

KUKA EtherNet/IP (Implicit Messaging)

Supported Series: KR C4 COMPACT

Website: <https://www.kuka.com/>

HMI Setting:

Parameters	Recommended	Options	Notes
PLC type	KUKA EtherNet/IP (Implicit Messaging)		
PLC I/F	Ethernet		
Port no.	44818		
Timeout	5		
Turn around delay	0 (ms)		
Requested Packet Interval	50 (ms)		
Assembly instance	Input:101 Size:64 Output:102 Size:64		

Online simulator	YES
-------------------------	-----

Assembly instance:

Input: Set the device to read back the instance number of the input buffer under Assembly (0x04).

Output: Set the device to write the instance number of the output buffer under Assembly (0x04).

Size:

Input: Set the device to read back the buffer size of the input buffer under Assembly (0x04).

Output: Set the buffer size that the device writes to the output buffer under Assembly (0x04).

Device Address:

Bit/Word	Device type	Format	Range	Memo
B	Input_8Bit	DDDo	0 ~ 5127	
B	Output_8Bit	DDDo	0 ~ 5127	
W	Input	DDD	0 ~ 512	
W	Input_Overflow	DDD	0 ~ 512	
W	Input_Byte	DDD	0 ~ 512	
W	Output	DDD	0 ~ 512	
W	Output_Overflow	DDD	0 ~ 512	
W	Output_Byte	DDD	0 ~ 512	

Wiring Diagram:

Ethernet cable

