

## YASKAWA MP Series Memobus (Ethernet)

Supported Series: YASKAWA MP2200, MP2300, MP2300S, MP9xx with 218IF-02 ethernet module.

Website: <http://www.yaskawa.com/>

### HMI Setting:

Parameters	Recommended	Options	Notes
<b>PLC type</b>	YASKAWA MP Series Memobus (Ethernet)		
<b>PLC I/F</b>	Ethernet		
<b>Port no.</b>	502		

### PLC Setting:

How to connect one Yaskawa Ethernet device with multiple HMIs?

[http://www.weintek.com/Download/MT8000/eng/FAQ/FAQ\\_61\\_How\\_to\\_connect\\_Yaskawa\\_Ethernet.pdf](http://www.weintek.com/Download/MT8000/eng/FAQ/FAQ_61_How_to_connect_Yaskawa_Ethernet.pdf)

### Device Address:

Bit/Word	Device type	Format	Range	Memo
B	MB	DDDDh	0 ~ 65534F	
B	IB	HHHHH	0 ~ A7FFF	Read only
B	IW_Bit	HHHHdd	0 ~ A7FF15	Read only
W	IW	HHHH	0 ~ A7FF	Read only
DW	IL	HHHH	0 ~ A7FF	Read only
DW	IF	HHHH	0 ~ A7FF	Float , Read only
W	MW	DDDDD	0 ~ 65534	
DW	ML	DDDDD	0 ~ 65533	
DW	MF	DDDDD	0 ~ 65533	Float

## Wiring Diagram:

### Ethernet cable

